



**The following simple instructions MUST be completed to ensure successful setup of your device**

**PLEASE CALL TO ACTIVATE YOUR DEVICE**

**Activation Line:**

Monday – Friday 9:00am – 5:00pm: 1-800-894-8074

**Setup Process**

1. **Remove your unit from the Box**
2. **Charge the Unit:** Plug the home charger into the jack located on your device. This is marked by a small rubber stopper with a lightning bolt on it. Please allow at least 4 hours to charge the device to full.
3. **Place your device in an area open to sky:** Turn on your device and put it in a window or an open area that has access to the sky. The unit will now look for a cell tower to connect to as well as a satellite signal. This can take up to 15 minutes for its first time turning on; please be very patient during this critical setup stage.
4. **Initial Light Sequence:** The startup light will stay BLUE for about 2 minutes, then start blinking GREEN slowly 4 times as it registers with your local cellular towers. When the device flashes alternatively RED and GREEN your device will be connected to both satellite and cellular coverage.
5. **Activate Account** – Please activate your account by calling the activation line and speaking with one of our friendly support agents.
6. **Login to your web software** – After activating please login to your web software online at the following web address

[webpanel.gemteksales.com](http://webpanel.gemteksales.com)

**Customer Support**

[support@geminitracking.com](mailto:support@geminitracking.com)

Monday – Friday 9:00am – 5:00pm: 1-800-894-8074



**On/Off** -- button is hidden under rubberized casing. To turn on/off, gently press just below the slightly raised microphone and above the seam.

**G Button** -- To activate/deactivate the Geofence feature from the tracker

**P Button** -- To activate/deactivate the Motion Sensor (parking) feature on the tracker

**S Button** -- To send an SOS alert signal to the control panel